

Application:

I/O module for connection to TROVIS 6610 CPU Module



The I/O module records the analog and digital input signals of connected sensors. Digital signals are transmitted over the bus to be processed by the CPU module. The data recorded by the CPU module are, in turn, transmitted by the I/O module as analog or digital signals to the control valves.

The I/O module provides 20 physical channels of which 10 are universal inputs for use with either analog or binary signals.

- Analog inputs as Pt 1000 (2-wire), 0 to 10 V DC or 0 to 2000 Ω inputs
- Binary inputs optionally as normally closed or normally open contacts, status indicated by LEDs, binary inputs 1 and 2 as counter inputs (1 kHz)
- 6 binary outputs including 250 V AC/3 A (resistive) coupling relay, status indicated by LEDs
- 4 analog 0 to 10 V DC outputs

Interfaces

- I/O bus (RS-485)

Further properties

- Power supply and I/O bus are electrically isolated from the module
- Inputs and outputs can be directly connected to the module's terminals
- LEDs indicate activity and failure of the module



Fig. 1 · TROVIS 6620 I/O Module

Technical data

TROVIS 6620 I/O Module	
Supply voltage	24 V AC, 50 Hz
Power consumption	Approx. 6 VA
Operating temperature	0 to 55 °C
Transport and storage	-20 to 70 °C
Relative humidity	Normal, no dew formation
Noise emission	According to EN 61000-6-3
Noise immunity	According to EN 61000-6-2
Degree of protection	IP 20 according to EN 60529
Mounting	On 35 mm rail (all DIN and EN types)
Dimensions (width x height x depth)	110 x 130 x 55 mm including terminals
Weight	0.5 kg

